

SPEED REGULATORS FOR FANS IP55 PROTECTION CASING

Regulators mod. RVM-RVT(adjustable voltage)

INPUT.VOLTAGE

OUTPUT VOLT.

MOTOR POWER

POWER VA24h

CONT. CURRENT

START. CURRENT

PROTECTION

F=FUSE AMP.

A=AUTOMATIC

S=MOTOR PROTECT

A=AUTOM.

S=SALVAM.

ADDIT. SWITCH External Lamps

P=WALL

DIMENSIONS mm. L

EXTERNAL H

I-h-depth P

WEIGHT Kg. Kg.

SINGLE-PHASE											THREE-PHASE			Inverter
RVM4E	RVM4I	RVM6E	RVM6I	RVM6LE	RVM6LI	RVM9E	RVM9LE	RVM12E	RVM12LE	RVM16E	RVT6E	RVT10E	RVT16E	RVTF5E
230	230	230	230	230	230	230	230	230	230	230	400+N	400+N	400+N	230-mon/Trif.
75-227	75-227	75-227	75-227	75-227	75-227	75-227	75-227	75-227	75-227	75-227	80-395	80-395	80-395	Trif. 230
370	370	750	750	750	750	1100	1100	1800	1800	2500	2200	3000	5500	1500
900	900	1350	1350	1350	1350	2000	2000	2600	2600	3500	4000	6500	10000	1900
4	4	6	6	6	6	9	9	12	12	16	6	10	16	5
10	10	10	10	10	10	15	15	15	15	40	16	40	40	10
F10	F10	F10	F10	F10	F10	F15	F15	F15	F15	A16	S4-6.3	S6-10	S10-16	electronics
10	10	10	10	10	10	15	15	15	15	-	-	-	-	-
-	-	-	-	-	-	-	-	-	-	16	40	40	40	-
-	-	-	-	-	-	-	-	-	-	-	4 - 6,3	6 - 10	10 - 16	-
NO	NO	NO	NO	SI	SI	NO	SI	NO	SI	NO	NO	NO	NO	NO
P	I	P	I	P	I	P	P	P	P	P	P	P	P	P
96	122	128	152	128	152	128	128	128	128	105	105	105	105	105
80	87	80	87	80	87	165	165	165	165	258	337	337	430	430
59	55	59	55	59	55	59	59	59	59	110	115	115	115	115
0,20	0,20	0,25	0,25	0,25	0,25	0,70	0,70	0,91	0,91	1,00	1,40	1,40	1,55	2,00

